

EE 483/583 Antennas for Wireless Communications (Spring 2022)

Homework 4

Monday, February 7, 2022

- 1) If the vector electric potential for an antenna is $\bar{F} = \hat{a}_z F_0 \frac{e^{-jkr}}{r}$, find $\bar{E} = \bar{E}_{FF}$ and $\bar{H} = \bar{H}_{FF}$ in the **far-field**. Give your answers in spherical coordinates. Assume $\bar{A} = 0$. Factor out common terms, e.g., $F_0 \frac{e^{-jkr}}{r}$.
- 2) Given that the vector magnetic potential for an antenna is $\bar{A} = \hat{a}_\theta A_0 \cos\theta \left[\frac{e^{-jkr}}{r} + \frac{jke^{-jkr}}{r^2} \right]$, find \bar{E} and \bar{H} **everywhere**. Give your answers in spherical coordinates. Assume $\bar{F} = 0$. Factor out common terms, e.g., $A_0 \frac{e^{-jkr}}{r}$.
- 3) Given that the vector magnetic potential for an antenna is $\bar{A} = \hat{a}_\theta A_0 \cos\theta \left[\frac{e^{-jkr}}{r} + \frac{jke^{-jkr}}{r^2} \right]$, find $\bar{E} = \bar{E}_{FF}$ and $\bar{H} = \bar{H}_{FF}$ in the **far-field**. Give your answers in spherical coordinates. Assume $\bar{F} = 0$. Factor out common terms, e.g., $A_0 \frac{e^{-jkr}}{r}$.
- 4) EE 583 only- If the vector electric potential for an antenna is $\bar{F} = \hat{a}_z F_0 \frac{e^{-jkr}}{r}$, find \bar{E} and \bar{H} **everywhere**. Give your answers in spherical coordinates. Assume $\bar{A} = 0$. Factor out common terms, e.g., $F_0 \frac{e^{-jkr}}{r}$.

Due Friday, February 11, 2022.