

EE 483/583 Antennas for Wireless Communications (Spring 2022)

Homework 2

Wednesday, January 26, 2022

- 1) 2.33a, d, & h. Assume $E_y = 1$ V/m. Also, in each case, write-out a time-domain equation for the electric field, plot the polarization ellipse with wave propagating into page, annotate RH/LH instead of CW/CCW, and find tilt angle with respect to the $+E_y$ -axis.
- 2) 2.37 For plots, $E_0 = E_a = 1$ V/m. For part (a), write-out a time-domain equation for the electric field, plot the polarization ellipse w/ wave propagating out of page, annotate RH/LH, and find tilt angle with respect to the $+E_y$ -axis. For part (b), write-out a time-domain equation for the electric field, plot the polarization ellipse w/ wave propagating into page, annotate RH/LH, and find tilt angle with respect to the $+E_y$ -axis. For part (c), also find $\hat{\rho}_w$ & $\hat{\rho}_a$.
- 3) 2.44 In addition, sketch the polarization ellipse of the wave for wave propagating into page assuming $E_x = E_y = 1$ V/m and find $\hat{\rho}_w$.
- 4) 2.53 Assume loss resistance is 2Ω . Hint: Look at Chapter 4 section on $\lambda/2$ dipoles.
- 5) 2.53 Assume loss resistance is 2Ω and the generator has a lossless 50Ω transmission line of length 1.65λ connecting it to the antenna.
- 6) 2.57 with length changed to $\lambda/50$ and radius to $\lambda/250$. Hint: Look at Chapter 4 section on infinitesimal dipoles.
- 7) EE 583 only:
A plane wave $\vec{\mathcal{E}} = \hat{a}_x 80 \cos(\omega t + 20^\circ - \beta y) + \hat{a}_z 60 \cos(\omega t - 40^\circ - \beta y)$ (V/m) is incident on an infinitesimal dipole located at the origin and oriented along the z -axis. What direction is the plane wave traveling? Sketch the polarization ellipse of the plane wave w/ wave propagating into page and annotate with its polarization. What are $\hat{\rho}_w$, $\hat{\rho}_a$, and the PLF when $\theta = 90^\circ$ and $\phi = 30^\circ$? [Hints: Look at Chapter 4 and remember how to convert from spherical to Cartesian unit vectors.]
- 8) EE 583 only: 2.68 Assume a lossless 75Ω transmission line of length 1.7λ connects source and dipole (Hint: look at Chapter 4 section on $\lambda/2$ dipoles.)

Due Wednesday, February 2, 2022.